



Job Name/Title: _____ Catalog Number _____
Contractor: _____ Notes: _____

LED Linear SHOP LIGHT



Get Back to Work with a Brighter Shop

Topaz's Shop Light is the durable LED solution to replace old Fluorescent tubes in garages, workshops, utility rooms and is low-profile for use in basements and attics. To make installation quick and easy, this fixture features integrated tubes, built-in on/off pull chain, is linkable and come with a five-foot power cord, hanging chains and V-hooks for suspension mounting.

FEATURES

- Integrated LED tubes
- Steel housing with polycarbonate end caps
- Built-in on/off pull chain
- Linkable up to 4 fixtures
- Includes 5' power cord with plug, two 12" hanging chains, two screw hooks and two V-hooks

SUGGESTED APPLICATIONS

- Garages
- Utility rooms
- Work shops
- Basements
- Attics





Job Name/Title: _____ Catalog Number _____
Contractor: _____ Notes: _____

LED Linear SHOP LIGHT

GENERAL SPECIFICATIONS

Input Voltage, Frequency: 120V, 60Hz

Power Factor: > 0.9

Efficacy: 95 LPW

Dimmable: No

CRI: 80

Beam Angle: 115°

SDCM: 6

Functional Life (L70): 50,000 hours

Location Rating: Damp

Ambient Operating Temperature: -4°F to 104°F

Suspension Mount up to 12 feet with included accessories

ITEM SPECIFICATIONS / ORDER INFO

Catalog Number	Order Code	UPC	Lumens	Wattage	Input Current	CCT
SHL/42W/40K/120V-98	70980	751338039001	4,000	42W	0.43A	4000K

NOMENCLATURE

Example: **SHL/42W/40K/120V**

SHL = Shop Light / **42W** = 42 Watt / **40K** = 4000K / **120V** = Voltage

ENERGY SAVINGS

Catalog Number	LED Wattage	Fluorescent Replacement Wattage	Watts Saved	Yearly Savings	5 Year Savings
Based on 12 hours/day and \$0.11/kWh					
SHL/42W/40K/120V-98	42W	2x32W T8	22W	\$11	\$53

PRODUCT DIMENSIONS / LINE DRAWING

Catalog Number	(A)	(B)	(C)	Weight
SHL/42W/40K/120V-98	47.99"	5.24"	1.91"	2.65 Lbs.



NOTES:

Specifications subject to change without prior notice. Replacement wattage shown depends on application and fixture.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

WARNING: Some products included in this specification sheet may be subject to the warning requirements of California's Proposition 65. Please refer to your product packaging for more information.

Revised February 2021